

50 Ohm BNC Female to 75 Ohm RCA Jack Adapter



RF Adapters Technical Data Sheet

ET1213

Configuration

- BNC Female Connector 1
- RCA Jack Connector 2

- 50 Ohms, 75 Ohms
- Straight Body Geometry

Features

BNC Interface compliant with MIL-C-39012

Nickel Plated Brass Contact

Applications

Allows Connection Between Series

General Purpose Test

Description

Ebeestock's ET12137 50 ohm BNC female to 75 ohm RCA jack adapter is part of our full line of RF components available for same-day shipping. Our BNC to RCA adapter has a female to jack gender configuration. ET12137 BNC female to RCA jack adapter operates to 250 MHz.

RF adapters are often used to enable connections between two connector types that would otherwise not mate. Certain adapter configurations can also be used to protect connectors on expensive equipment where the number of connect/ disconnect cycles is high. An RF, microwave or millimeter wave adapter is connected to the equipment, and the commonly changed connection is made with the adapter which can be easily replaced when it wears out after high usage; such adapters are referred to as connector savers. Ebeestock also offers bulkhead, panel mount, hermetically sealed, reverse polarity, and isolated ground adapter varieties to serve all of your RF, microwave and millimeter wave needs.

Electrical Specifications Frequency Range MHz Operating Voltage (AC) 500 Vrms

Electrical Specification Notes: Values at 25°C, sea level.

Mechanical Specifications

Size

1.19 in [30.23 mm] Length Width 0.44 in [11.18 mm] Weight 0.02 lbs [9.07 g]

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: 50 Ohm BNC Female to 75 Ohm RCA Jack Adapter ET12137

www.ebeestock.com



50 Ohm BNC Female to 75 Ohm RCA Jack Adapter



RF Adapters Technical Data Sheet ET12137

Description	Connector 1	Connector 2
Type	BNC Female	RCA Jack
Polarity	Standard	Standard
Interface Specification	MIL-C-39012	
Mating Cycles	500	

Material Specifications

Description	Connector 1		Conne	ctor 2
	Material	Plating	Material	Plating
Туре	BNC Female		RCA Jack	
Contact	Brass	Nickel	Brass	Nickel
Insulation	PTFE		PTFE	
Outer Conductor	Brass	Nickel	Brass	Nickel
Outer Conductor	Brass	Nickel	Brass	Nickel

Environmental Specifications

Temperature

Operating Range -40 to +60 deg C

Vibration MIL-STD-202, Method 204, Condition B
Temperature Cycling MIL-STD-202, Method 107, Condition B
Salt Spray MIL-STD-202, Method 101, Condition B

Compliance Certifications (see product page for current document)

Plotted and Other Data

Notes:

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: 50 Ohm BNC Female to 75 Ohm RCA Jack Adapter ET12137



50 Ohm BNC Female to 75 Ohm RCA Jack Adapter



RF Adapters Technical Data Sheet ET12137

50 Ohm BNC Female to 75 Ohm RCA Jack Adapter from Ebeestock Enterprises has same day shipment for domestic and International orders. Our RF, microwave and millimeter wave products maintain a 99% availability and are part of the broadest selection in the industry.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: 50 Ohm BNC Female to 75 Ohm RCA Jack Adapter ET12137

URL: https://www.ebeestock.com/50-ohm-bnc-female-to-75-ohm-rca-jack-adapter-0012137

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Ebeestock reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Ebeestock does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Ebeestock does not assume any liability arising out of the use of any part or documentation.

ET12137 CAD Drawing
50 Ohm BNC Female to 75 Ohm RCA Jack Adapter

