

COMPONENTS	IMPEDANCE
FAKRA PLUG	50 OHM
SMA MALE	50 OHM
ET-C100	50 OHM

Standard Lengths

-12	12"
-24	24"
-36	36"
-48	48"
-60	60"
-XXX	Custom Length in Inches

Part Configurator

1. Replace Y with code.
2. Replace XX with length in inches.

CODING	PLUG	COLOR	APPLICATION
A	6	BLACK	RADIO WITH PHANTOM SUPPLY
B	7	WHITE	RADIO WITHOUT PHANTOM SUPPLY
C	2	BLUE	GPS: TELEMATICS OR NAVIGATION
D	2	BORDEAUX	GSM: CELLULAR PHONE
H	2	VIOLET	GPS: TELEMATICS AND NAVIGATION
I	2	BEIGE	BLUETOOTH
K	2	CURRY	RADIO WITH IF OUTPUT (ANTENNA DIVERSITY)
Z	d	WATER BLUE	NEUTRAL CODING

LENGTH MEASURED FROM CONTACT TO CONTACT

FAKRA PLUG

cMI 二

5/16
HEX

SMA
MALE



8th Floor, Building 1, Yongfu Science and Technology Center Industrial Park, Nanzha District 5, Humen, 523900, Dongguan, Guangdong, China.

Website: www.ebeestock.com

Email: sales@ebeestock.com

COAXIAL & FIBER OPTICS

DWG TITLE	ET22424	DES_	sma-male-to-bordeaux-fakra-plug-cable-12-inch-length-using-pe-c100-lsz-h-coax-0022420
-----------	---------	------	---

SIZE A | FSCM NO. 53919 | CAD FILE 073102 | SCALE N/A | 127

NOTES:

1. UNLESS OTHERWISE SPECIFIED ALL DIMENSIONS ARE NOMINAL.
2. ALL SPECIFICATIONS ARE SUBJECT TO CHANGE WITHOUT NOTICE AT ANY TIME.