

TNC Male to FME Jack Adapter



# RF Adapters Technical Data Sheet

ET1234

3

## Configuration

- TNC Male Connector 1
- FME Jack Connector 2

- 50 Ohms
- Straight Body Geometry

### Features

- TNC Interface compliant with MIL-STD-348A
- FME Interface compliant with MIL-STD-348A
- Gold Plated Brass Contact
- 30 µ-in min Gold Contact Plating

## Applications

- Allows Connection Between Series
- General Purpose Test

#### Description

Ebeestock's ET12343 TNC male to FME jack adapter is part of our full line of RF components available for same-day shipping. Our TNC to FME adapter has a male to jack gender configuration.

RF adapters are often used to enable connections between two connector types that would otherwise not mate. Certain adapter configurations can also be used to protect connectors on expensive equipment where the number of connect/disconnect cycles is high. An RF, microwave or millimeter wave adapter is connected to the equipment, and the commonly changed connection is made with the adapter which can be easily replaced when it wears out after high usage; such adapters are referred to as connector savers. Ebeestock also offers bulkhead, panel mount, hermetically sealed, reverse polarity, and isolated ground adapter varieties to serve all of your RF, microwave and millimeter wave needs.

## Mechanical Specifications

Size Length Width Weight	0.57 in [14.48	1.291 in [32.79 mm] 0.57 in [14.48 mm] 0.048 lbs [21.77 g]	
Type	TNC Male	FME Jack	
Polarity Interface Specification	Standard MIL-STD-348A	Standard MIL-STD-348A	

Material Specifications							
	Connector 1		Connector 2				
Туре	TNC Male		FME Jack				
Contact	Brass	Gold	Brass	Gold			
		30 μ-in minimum		30 μ-in minimum			
Insulation	PTFE		PTFE				

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: TNC Male to FME Jack Adapter ET12343

8th Floor, Building 1, Yongfu Science and Technology Center Industrial Park, Nanzha District 5, Humen,523900, Dongguan, Guangdong, China.



TNC Male to FME Jack Adapter



# RF Adapters Technical Data Sheet ET12343

			100 μ-in minimum
Brass	Nickel		
	100 μ-in minimum		
Silicone			
Brass	Nickel		
	100 μ-in minimum		
	Silicone	100 μ-in minimum Silicone Brass Nickel	100 μ-in minimum  Silicone  Brass Nickel

#### Compliance Certifications (see product page for current document)

TNC Male to FME Jack Adapter from Ebeestock Enterprises has same day shipment for domestic and International orders. Our RF, microwave and millimeter wave products maintain a 99% availability and are part of the broadest selection in the industry.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: TNC Male to FME Jack Adapter ET12343

URL: https://www.ebeestock.com/tnc-male-to-fme-jack-adapter-0012343

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Ebeestock reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Ebeestock does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Ebeestock does not assume any liability arising out of the use of any part or documentation.

